

\mathbb{H}

*GENERAL_ HDISTWAY MUST BE IN ACCORDANCE WITH SAFETY CODE FOR ELEVATORS (ASME A17.1 OR B44-2000) AND ALL STATE/PROVINCIAL AND LOCAL CODES.

PLUMB HDISTWAY- DUE TO CLOSE RUNNING CLEARANCES OWNER/AGENT MUST ENSURE THAT HDISTWAY AND PIT (WHERE PROVIDED) ARE LEVEL, PLUMB AND SQUARE AND ARE IN ACCORDANCE WITH THE DIMENSIONS ON THESE DRAWINGS.

VERHEAD CLEARANCE- DWNER/AGENT MUST ENSURE MINIMUM CLEARANCE IS IN COMPLIANCE WITH CODES.

PATCH AND

CONTRACTOR/CUSTOMER TO VERIFY ALL DIMENSIONS AND REPORT ANY DISCREPANCIES TO OUR OFFICE IMMEDIATELY.

TURAL

<u>UPPORT WALL LOADS</u> STRUCTURAL ENGINEER TO ASSURE SILDING AND SHAFT WILL SAFELY SUPPORT ALL LOADS BY THE LIFT EQUIPMENT. REFER TO THE TABLES ON THIS FOR LOADS IMPOSED BY THE EQUIPMENT.

UITABLE LINTELS MUST BE PROVIDED BY OWNER/AGENT. MES ARE NOT DESIGNED TO SUPPORT OVERHEAD WALL

*MACHINE ROOM

IN / ACCESS-_ MACHINE ROOM LOCATED AT THE LOWEST ADJACENT TO HOISTWAY, UNLESS SHOWN OTHERWISE ON THE DRAWINGS. FIELD ADJUSTMENT BY INSTALLER MAY BE RY TO MEET JOB SITE CONDITIONS OR REGULATIONS. ACCESS INE ROOM TO BE THROUGH A SELF CLOSING AND SELF DOOR.

.CSNDI <u>FOR DIL & ELECTRIC LINES</u> PROVIDED BY DTHERS, FROM

		-			
	15		15	115/1PH	STH
21	40		60	230/1PH/60HTZ	
15.6	30		30	NFO 208/3PH/60HTZ	NF-
CURRENT (AMPS)	FUSE (AMPS)	FUS	SIZE (AMPS)	(V/PH/CYCLE)	
DELAY FULL LOAD	E DELAY	TIME	DISCONNECT	INPUT VOLTAGE	

*ELECTRICAL

JPPLY- (SEE SPECIFICATIONS) LOCKABLE FUSED DISCONNECT (ILIARY CONTACT TO BRAKE THE BATTERY FEED, OR CIRCUIT) WITH A 3-POLE BREAKER FOR BATTERY FEED REQUIRED, IANCE WITH ELECTRICAL CODE, AS FOLLOWS:

ON WALL ON LOCK JAMB SIDE OF MACHINE ROOM DOOR)

POWER MUST BE SUPPLIED. . OWNER/AGENT TO ENSURE AT LEAST 5 FTC OR 54 LUX .IGHTING OVER ELEVATOR AREA. POWER- BEFORE INSTALLATION CAN BEGIN, PERMANENT

FASCIA PANEL BELOW UPPER LEVEL ENTRANCE— WHERE REQUIRED, FASCIA PANEL MUST BE FASTENED TO A SOLID WALL AND BE PERPENDICULAR TO THE FLOOR AND WALLS. HOISTWAY FASCIA IS NOT SELF-SUPPORTING FOR LONG, CONTINUOUS RUNS VOID OF ENTRANCES. ADEQUATE SUPPORT AND THE FASCIA MUST BE PROVIDED BY OTHERS.

ADEQUATE ROUGH OPENING. <u>ASSEMBLIES</u> ENTRANCE ASSEMBLIES MUST BE ADJUSTED WITH PLATFORM AND INTERLOCK EQUIPMENT. OTHERS TO

REV-000

RION MODEL 4260